



Sunell 32ch NVR list

تیرماه ۱۴۰۵



	32 Ch 2HDD NVR
Model	SN-NVR3832E2 (NVR32L.N)
Picture	
Audio and Video	
IP Camera Input	32 Channel
Audio I/O	1/1, RCA
Display	
Interface	1 HDMI, 1 VGA
Resolution	HDMI: 3840 × 2160, 1920 × 1080, 1280 × 1024, 1024 × 768
	VGA: 1920×1080, 1280×1024, 1280×720
Decoding Capacity	1ch 12MP, 4ch 4MP, 8ch 1080P, 16ch D1, 32ch D1
Multi-screen Display	1/4/9/16/32
Recording	
Compression	H.265+/ H.265/H.264+/H.264
Resolution	12MP, 8MP, 6MP, 5MP, 4MP, 3MP, 1080P, 720P, D1 etc.
Record Rate	Up to 160 Mbps/80 Mbps incoming/outgoing bandwidth
Record Mode	Manual, Schedule (Regular, Continuous), Event
Playback and Backup	
Sync Playback	16/9/4/1
Search Mode	Time /Date, Alarm, Picture grid, Event
Playback Function	Play, Pause, Stop, Rewind, Fast play, Slow Play, Next File, Previous File, Next Camera, Previous Camera, Full Screen, Shuffle, Backup Selection, Digital Zoom
Backup Mode	USB Device, Network
Alarm	
General Alarm	Motion Detection, Video Loss, Alarm in, Alarm out
Intelligent Analysis (By Camera)	Smoking Detection, Smoke and Fire Detection, Fire Spot Detection, Intrusion, Single Line Crossing, Double Line Crossing, Loitering, Wrong-way, Illegal Parking, People Counting, Smart motion, detection, Enter Area, Leave Area, etc.
Abnormal Alarm	Disk Alarm, IP Address Conflict, Network Disconnect
Network	
Network Function	HTTP, HTTPS, TCP/IP, IPv4/IPv6, UPnP, UDP, RTSP, SMTP, NTP, DNS, DHCP, P2P, IP Filter, DDNS, 802.1X, SNMP, 3G/4G, PPPoE
Max. User	8 users
Interoperability	ONVIF 2.4, SDK, CGI
P2P	Support
Storage	
Internal HDD	2 SATA interfaces, up to 12TB capacity for each disk
ANR	Support
Disk Group	Support
eSATA	N/A
Interface	
USB	Front panel: 2 × USB 2.0
Interface	2 × RJ-45, 10/100/1000 Mbps self-adaptive Ethernet port
PoE Interface	N/A
PoE Max Power	N/A
Alarm In/Out	8/1
Reset Button	On-board reset button
General	
Power Supply	DC12V/3A
Power Consumption	< 15W (without HDD)
Operating Conditions	-10 °C ~ 50 °C (14 °F ~ 122 °F)
Dimensions	372×310.5×46.5mm
Net Weight	1.8 kg (No disk)